

EMERGENCY LIGHTING SYSTEM WITH AUTOMATIC DIAGNOSTIC TEST

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] Not applicable

5

FEDERALLY SPONSORED RESEARCH

[0002] Not applicable.

SEQUENCE LISTING, ETC ON CD

10 [0003] Not applicable.

BACKGROUND OF THE INVENTION

Field of the Invention

[0004] This invention relates to emergency lighting systems that provide
15 illumination for buildings and the like during power failure, using an emergency
power source and selected fixtures or luminaires within a larger lighting system.

Description of Related Art

[0005] In the past, safety codes required that emergency luminaires that are
20 powered by an emergency generator or inverter during a power outage must be
illuminated 24 hours per day, 7 days per week, to give a continual indication of
their readiness and operability. In recent times, the codes have been changed to
permit the use of a power transfer control (listed under UL924 specs) to turn on
and off both the regular and emergency luminaires at the same time. During a

utility power failure or room power interruption, only the designated emergency luminaires are illuminated automatically, using the emergency power source, regardless of the on/off position of the room lighting switch.

[0006] This arrangement is more economical and convenient, but it does not

5 provide the continuing assurance of emergency lighting readiness that was given by the older systems. As a result, it is necessary to provide a test feature and readiness indication for systems that use the power transfer control arrangement.

Generally, this requirement is met by turning off the lighting branch circuit breaker that serves a particular area, which in turn automatically transfers the
10 emergency light fixtures in that area to an emergency power source. This test routine involves visiting each lighting panel, and is time consuming.

[0007] Intelligent building operating systems may incorporate sensors and subroutines to survey the emergency lighting systems in a building, and report problems or failures. These systems, however, may not fulfill code requirements

15 for personal inspection of the systems and the individual responsibility it conveys. Nor do they provide the conclusive determination of eyewitness observation of proper testing of an emergency lighting system.

BRIEF SUMMARY OF THE INVENTION

[0008] The present invention generally comprises an emergency lighting system that employs a power control transfer switch to power all the luminaires of a lighting system during normal use, and to switch to an emergency power source and power some of the luminaires during a power outage. A salient feature of the invention is that the wall switch that controls the luminaires for regular use also serves to carry out an automatic system test routine every time it is used by the room or building occupants. This aspect of the invention may be applied to common lighting system connection schemes.

10 [0009] Whenever the wall switch is turned off, the invention performs a quick test of the emergency lighting system. First, the regular (non-emergency luminaires) are extinguished, and the emergency luminaires are activated for a time-limited period. After a few seconds, the emergency luminaires are then extinguished, and the system is off. During the brief operation of the emergency
15 luminaires, it is easy to observe that: 1) emergency power is available to the emergency lighting system; and, 2) the emergency luminaires are functioning properly. It is significant to note that this test is carried out whenever the wall switch is turned off, so that the testing procedure becomes a routine aspect of the use of the lighting system. Thus the system is tested on a continuing basis,
20 leading to a greater awareness of the emergency lighting system and its ready status.

[0010] The automatic test feature also provides a serendipitous benefit, in that it illuminates the room or area for a brief period after the switch is turned off, during which time the occupants may leave the room or area before total darkness

ensues. In many situations this added benefit may provide enhanced safety during egress.

[0011] The electronic assembly of the invention may be mounted directly behind the wall switch within the same box, or it may be mounted in a luminaire or in any
5 wall or ceiling mounted junction box. No matter where it is mounted, the automatic test feature is continuously available. Unlike prior art emergency lighting systems, it is not necessary to gain access to the circuit breaker panel in order to perform a test routine, so that the emergency lighting system may be tested with no disruption to other activities carried out in the lighted space.

BRIEF DESCRIPTION OF THE DRAWING

[0012] Figure 1 is a block diagram of the connections to the emergency lighting system with automatic diagnostic testing of the present invention.

[0013] Figure 2 is a schematic of an embodiment of a circuit for carrying out the
5 emergency power switching and automatic diagnostic testing functions of the present invention.

[0014] Figure 3 is an exploded view showing the apparatus of the invention installed in a ceiling junction box.

[0015] Figure 4 is a perspective view showing the apparatus of the invention
10 installed in a luminaire.

[0018] Figure 5 is an exploded view showing the apparatus of the invention installed in a wall switch junction box.

DETAILED DESCRIPTION OF THE INVENTION

[0016] The present invention generally comprises an emergency lighting system that employs a power control transfer switch to deliver regular utility power to all the luminaires of a lighting system during normal use, and to switch to an

5 emergency power source and power at least some of the luminaires during a power outage. A significant feature of the invention is that the wall switch that controls the luminaires for regular (everyday) use also serves to carry out an automatic system test routine every time it is used by the room or building occupants. That is, whenever the lights are switched off while being driven in
10 usual fashion by regular utility power, the designated emergency luminaires are lighted for a brief period, on the order of 15 seconds. Thus the occupants are apprised of the operability of the emergency luminaires, and the fact that the emergency power source (generator, battery, etc.) is properly available to drive the emergency luminaires.

15 [0017] With regard to Figure 1, the emergency lighting system of the invention includes an electronic assembly 11 that is connected to the regular utility power system, including the hot and neutral lines as well as a switched line operated by a room switch. Note that the regular load, such as one or more luminaires used to light a room or space, is connected from the switch leg to the neutral leg of the
20 regular power system. Also, it may be appreciated that the switch leg may alternatively include an occupancy system (here shown as normally open contacts C-1) or other similar control features known in the prior art. The assembly 11 is also connected to an emergency power system through a transfer switch operating in accordance with UL 1008 specs or the equivalent. The

emergency power system includes hot and neutral legs, with an emergency load connected therebetween that comprises one or more of the luminaires in the system .

[0018] During normal operation of the luminaires in the lighting system, the regular hot leg provides the operating voltage to the assembly, and the regular neutral leg is ground. When the regular operating voltage is interrupted or otherwise fails, the regular luminaires go off and relay contacts C-2 close. The emergency luminaire is thus connected between emergency hot and neutral legs, and is operated at full brightness, despite the fact that it may have been in a switched off condition prior to emergency power being switched on.

[0019] When regular power is restored and the regular hot leg is once again carrying the proper operating voltage, the relay contacts revert to the normal operating configuration and regular system power is supplied to the regular and emergency luminaires. Thus emergency power is switched into the designated emergency lighting whenever regular power is interrupted, and no maintenance work is required to reset the system.

[0020] A further significant aspect of the invention is the provision of an automatic test feature to assess the readiness of the emergency lighting luminaires and the emergency power supply. The test routine is operated automatically whenever the lighting system in regular operating mode is switched off, using the same wall switch (for room or area lamps) or the like that is normally used to turn the lighting system on and off. That is, whenever the regular on-off switch is turned off, the system switches to emergency test mode, and emergency power is supplied to the emergency luminaires while the regular luminaires are turned off.

This arrangement enables anyone to determine that the emergency fixtures are operational, and that emergency power is online and available.

[0021] The test phase is limited to a brief time period, on the order of 15-30 seconds, after which the emergency luminaire(s) are extinguished and the system
5 reverts to normal operation on regular utility power. The test also provides lighting during egress, in that when the lights are switched off the room or area will not be subject to immediate and total darkness; rather, the emergency fixtures will give more than adequate illumination for safe exit of the area.

[0022] One example of a circuit arrangement for providing the automatic test
10 feature is embodied in the circuit 11 of Figure 2, although modifications and other circuits may be devised to provide this function. When the room switch is on, capacitor C4 is charged, transistor Q4 is on, and capacitor C3 is charged. Transistor Q1 is turned on, and transistors Q2 and Q3 are off. Q3 off determines that relay coil RL1 is off, so that the normally closed relay contacts CR1 remain
15 closed, and emergency power is delivered to the emergency light (in addition to the regular lights being powered by the closed room switch).

[0023] When the room switch is turned off, transistor Q4 goes off, and C3 discharges through R4 to create a time delay of approximately 15 seconds. Then, transistor Q1 goes off, which switches Q2 and Q3 on, thus energizing relay coil
20 RL1. This action opens the normally closed relay contacts CR1, which turns off the emergency light (after the time delay). During the time delay period, Q4 and Q3 are off and Q5 is on, and LED1 is off. After the time delay period, Q3 goes on, Q5 turns off, and LED1 is illuminated.

[0024] Also, note that because the automatic diagnostic test feature of the invention provides an ongoing, frequent testing and affirmation of the emergency lighting system, it is generally not necessary to observe the indicators such as LED1 and LED2.

5 [0025] The automatic diagnostic test feature of the invention also greatly broadens the opportunities for installation of the assembly 11 described previously. Due to the fact that the regular on/off switch provides the test function, the assembly 11 may be mounted in a ceiling 22 in a junction box 21 sealed by a cover plate 23 (Figure 4), providing of course that all proper wiring
10 connections are made to the luminaires or fixtures, the wall switch, and the regular and emergency power sources, as described above and shown in the previous figures. Likewise, the assembly 11 may be mounted in a ceiling fixture or luminaire 24 (Figure 5), which may be one of the plurality of fixtures that are powered by the lighting system. The device 11 is sufficiently compact that it may
15 even be installed within the junction box 27 that houses the on/off wall switch 26, as shown in Figure 6. In all these installations the device 11 may not be readily available for visualization, but the automatic diagnostic function utilizing the wall switch and emergency luminaires fulfills all necessary test functions for the emergency system.

20 [0026] The foregoing description of the preferred embodiments of the invention has been presented for purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise form disclosed, and many modifications and variations are possible in light of the above teaching without deviating from the spirit and the scope of the invention. The embodiment

described is selected to best explain the principles of the invention and its practical application to thereby enable others skilled in the art to best utilize the invention in various embodiments and with various modifications as suited to the particular purpose contemplated. It is intended that the scope of the invention be

5 defined by the claims appended hereto.